

# ADJ H2O TWO - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
4Ch	9Ch		
1	1		<b><i>Dimmer (Intensity)</i></b>
		0 - 255	Intensity 0 to 100%
2	2		<b><i>Rotation</i></b>
		0 - 9	No Rotation
		10 - 120	Clockwise Rotation, fast to slow
		121 - 134	No Rotation
		135 - 245	Counter Clockwise Rotation, slow to fast
		246 - 255	No Rotation
3	3		<b><i>Colors</i></b>
		0 - 10	White
		11 - 21	White / Orange
		22 - 32	Orange
		33 - 43	Orange / Green
		44 - 54	Green
		55 - 65	Green / Blue
		66 - 76	Blue
		77 - 87	Blue / Yellow
		88 - 98	Yellow
		99 - 109	Yellow / Purple
		110 - 120	Purple
		121 - 127	Purple / White
		128 - 187	Clockwise Rotation, fast to slow
188 - 196	Stop		
197 - 255	Counter Clockwise Rotation, slow to fast		
	4		<b><i>Shutter, Strobe</i></b>
		0 - 31	LEDs Off
		32 - 63	LEDs On
		64 - 95	Strobe Effect, slow to fast
		96 - 127	LEDs On
		128 - 159	Pulse Effect in Sequences
		160 - 191	LEDs On
		192 - 223	Random Strobe Effect, slow to fast
224 - 255	LEDs On		
	5		<b><i>Auto Programs</i></b>
		0 - 10	Off
		11 - 26	Program 0
		27 - 43	Program 1
		44 - 60	Program 2
		61 - 76	Program 3
		77 - 255	No Function

# ADJ H2O TWO - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
4Ch	9Ch		
	6		<b><i>Auto Programs Speed</i></b>
		0 - 255	Slow to Fast Speed
	7		<b><i>Dim Mode</i></b>
		0 - 20	Default to Unit Setting
		21 - 40	Standard
		41 - 60	Stage
		61 - 80	TV
		81 - 100	Architectural
		101 - 120	Theatre
		121 - 140	Stage 2
			<b><i>Dim Speed</i></b>
		141	0.1s
		142	0.2s
		143	0.3s
		144	0.4s
		145	0.5s
		146	0.6s
		147	0.7s
		148	0.8s
		149	0.9s
		150	1.0s
		151	1.5s
		152	2.0s
		153	3.0s
		154	4.0s
	155	5.0s	
	156	6.0s	
	157	7.0s	
	158	8.0s	
	159	9.0s	
	160	10.0s	
	161 - 255	Default to Unit Setting	
	8		<b><i>Dim Curves</i></b>
		0 - 20	Square
		21 - 40	Linear
		41 - 60	Inv Squa
		61 - 80	S Curve
		81 - 255	No Function
4	9		<b><i>Special</i></b>
		0 - 10	No Function
		11 - 26	Reset All Motors
		27 - 255	No Function